



Resetting Jetsort 1000 / 3500 / 3600 / 4200 / 6400 parameters

1. Switch Jetsort ON
2. Make sure you are in a BATCH END status
3. Press and hold the RED STOP key until the SELECT SPECIAL MODE screen is displayed
4. Select ENTER SETUP MODE

NB: All options can be selected or deselected by touching the required box on the screen.

The correct settings for the Jetsort to enable data transfer to Quantum are:

Menu 1 - Enable Functions:

Sleep Mode	Off
End Subbat	Auto
Display at End	Total
Date	Off
(it is important to ensure the date is turned off)	
Default Limits	Full

Exit (to menu 1)

Menu 1 - Data Entry Selection:

Menu 2 - Select Labels

A	Off
B	Off
C	Auto
D	Off

Exit (to menu 2)

Menu 2 - Select Receipts

Curncy	Off
Chk/Cp	Off
Misc	Off

Exit (to menu 2)

Menu 2 - Select Other

ID	Off
Dbalb	Off
Dbalsb	Off

Exit (to menu 2)

Exit (to menu 1)

Menu 1 - Port Setup:

by default opens in Port 1 – use NEXT to see Port 2, etc.
 All other ports should be set to OFF
 Port 3, Prntr, 1200, 7, Odd – configuring for Printer
 Port 4, Comm, 4800, 7, Odd – configuring for data transfer through this port (an alternative port can be used but any other comm port must be removed first)

Exit (to menu 1)

Menu 1 - Peripheral Formats:

Menu 3 - Computer Interface

Emulate	36 2 (NOT 36 1)
Protcl	Immed
Ack	On **
Limrep	Off
Mode	NORML

Exit (to menu 3)

Menu 3 - Printer Format Setup

Mode	2
When	Auto
Dbrk	On
Color	Red1

Exit (to menu 3)

Exit (to menu 1)

Menu 1 – option 1 - User Defaults: Save Current as User Default

Exit from the SET-UP MENUS then the SELECT SPECIAL MODE MENU

*** Can be off but Jetsort will not inform if connection to PC/Handheld is lost*