Setting Up the Jetsort 3600/4200/6400 to Communicate with the QUANTUM System or Handheld Terminal

When using the Handheld or COINSORTER DOWNLOAD, you will need to reset the parameters on the Jetsort.

To reset the Jetsort 3500/3600/4200/6400 parameters:

Switch Jetsort ON
Make sure you are in a BATCH END status
Press and hold the RED STOP key until the SELECT SPECIAL MODE screen is displayed
Select ENTER SETUP MODE

NB All options can be selected or deselected by touching the required box on the screen.

The correct settings are:

Enable Functions:	Sleep Mode	Off
	End Subbat	Auto
	Display at End	Total
	Date	Off
	(it is important to ensure the date is turned off)	
	Default Limits	Full

Data Entry Selection:

Select Labels	A	Off
	B	Off
	C	Auto
	D	Off
Select Receipts	Curncy	Off
	Chk/Cp	Off
	Misc	Off
Select Other	ID	Off
	Dbalb	Off
	Dbalsb	Off

Port Setup:
Port 3, Prntr, 1200, 7, Odd
Port 4, Comm, 4800, 7, Odd
All other ports should be set to OFF

Peripheral Formats:

Computer Interface	Protcl	Immed
	Ack	On*
	Limrep	Off
Printer Format Setup	Mode	2
	When	Auto
	Dbrk	On
	Color	Red1
User Defaults:	Save Current as User Default	

Exit from the SET-UP MENUS then the SELECT SPECIAL MODE MENU
* Can be off but Jetsort will not inform if connection to PC/Handheld is lost.